4. Electrical Parts List

4-1 SVR-750/659/653/650/6503/557

Loc.No	Part No	Description ; Specification	Remark
-	-	**ASSY PCB-MAIN FULL;**	**S.N.A.**
S.M.P.S. PARTS			
BD1SD1	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SD2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
BD1SF1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
BD1SF2	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SF3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS1	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS2	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD03	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SD04	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SD11	2401-001682	C-AL;82uF,20%,400V,GP,BK,22x25,10	
C1SD12	2305-001029	C-FILM,MPEF;10nF,10%,630V,TP,12x9x12.5,5	
C1SD13	2201-000376	C-CERAMIC,DISC;0.22nF,5%,50V,SL,TP,6.3x3	
C1SF12	2401-001200	C-AL;33UF,20%,50V,WT,TP,6.3X11,2.5	
C1SS01	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS02	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS03	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SS12	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1kV,Y5P,TP,7x4,	
C1SS31	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS32	2401-003137	C-AL;330UF,20%,50V,WT,TP,10X16MM,5	
C1SS33	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS34	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS35	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS36	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C1SS39	2301-000129	C-FILM,PEF;100nF,5%,50V,TP,10X9X4.3X5,5m	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SD11	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SD31	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SF05	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SF12	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS31	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS32	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
IC1SF1	1203-001802	IC-PWM CONTROLLER;STR-G6551,TO-220F,5P,-	
IC1SS1	0604-000186	PHOTO-COUPLER;TR,-,200mW,DIP-4,ST	⚠
IC1SS2	AC14-12006D	IC;KA431Z,TO-92,TAPING	
L1SS02	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	⚠
L1SS31	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS32	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1SS1	AC26-00002C	TRANS SWITCHING;-,-,EE2621,-,UL/CSA/DEMK	⚠
R1SD12	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD13	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD14	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD15	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD16	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R1SD31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF15	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SF19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF20	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SF21	2001-000096	R-CARBON(S);1MOHM,5%,1/2W,AA,TP,2.4X6.4M	
R1SS03	2008-001033	R-FUSIBLE(S);10ohm,5%,2W,AF,TP,3.9x10mm	
R1SS10	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS11	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R1SS32	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R1SS33	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS34	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
VA1SS1	1405-001026	VARISTOR;470V,600A,9x7mm,TP	⚠
POWER DRIVE PARTS			
C1P102	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P103	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P104	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P105	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P106	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P108	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P120	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
D1P101	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P103	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
Q1P101	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P102	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P103	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P104	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
Q1P105	0504-000116	TR-DIGITAL;KSR1001,NPN,300MW,4.7K/4.7K,T	
R1P101	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	Other Models
	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SVR-557 Only
R1P102	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R1P104	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	Other Models
	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	SVR-6503 Only
R1P105	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R1P106	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P107	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R1P108	2001-000611	R-CARBON;3.9KOHM,5%,1/4W,AA,TP,2.4X6.4M	
R1P110	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R1P115	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
ZD1P04	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
STSTEM CONTROL/SERVO PARTS			
C601	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C602	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C605	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C607	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	Not Used SVR-557
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	SVR-6503 only
C609	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C620	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C622	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2	
C623	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C624	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	Not used SVR-557
C625	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	Not used SVR-557
C626	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C627	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C633	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C634	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C635	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C636	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C637	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
C638	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
C639	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C640	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C641	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C642	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C644	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
C646	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C650	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C651	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C652	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C655	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
C679	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C680	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C681	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C690	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C691	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C692	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C693	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	Not used SVR-557
C695	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
C697	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C698	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	SVR-750/659/653 Only
CN604	3711-004833	CONNECTOR-HEADER;BOX,12P,2R,2MM,STRAIGHT	
D601	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	SVR-659 Only
D603	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D605	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D612	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC601	AC09-00316A	IC MICOM;784927GF-232-3BA,SVR-653,100P,	Other Models
	AC09-00338A	IC MICOM;N128-A72-3BA,SV-655GX-01,100Pl	SVR-659 Only
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001148	IC-EEPROM;24C021,2KBIT,DIP,8P,300MIL,10M	Other Models
	1103-001150	IC-EEPROM;524C80D81,8KBit,DIP,8P,300MIL,	SVR-659 Only
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	Not used SVR-557
L602	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L603	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
LD601	0601-000517	LED-IR;RECTANGULA,4x6.0mm,75mW,6V,950	
PT601	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
PT602	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
Q601	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q603	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	SVR-750/659/653 Only
R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R605	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R613	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R631	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R632	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	Not used SVR-557
R637	2007-000947	R-CHIP;47OHM,5%,1/10W,DA,TP,2012	Not used SVR-659
R638	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R639	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R641	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R642	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R644	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R651	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012	
R656	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R657	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	Not used SVR-557
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R666	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R667	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R668	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R669	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R670	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R671	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R672	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R674	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2007-000738	R-CHIP;30KOHM,5%,1/10W,DA,TP,2012	
R678	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R679	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R680	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	Not used SVR-557
R682	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R685	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
R690	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R691	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R692	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	Not used SVR-557
R693	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R694	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R696	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R698	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RS601	AC34-20100B	SWITCH-REC;-,-,X-9,-	
S601	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
S602	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
SW601	AC34-20100A	SWITCH-MODE;-,-,X-9,-	
W062	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W064	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W066	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W140	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	Not used SVR-557
XT602	2801-003139	CRYSTAL-UNIT;8MHz,50ppm,28-AAA,22pF,80oh	
AUDIO/VIDEO PARTS			
C315	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C317	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C318	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C319	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,	
C320	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C321	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C322	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C324	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C325	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C326	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C327	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
C328	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C329	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C330	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C331	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C332	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C333	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C335	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C336	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	F/AV Option
C337	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C338	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C339	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C344	2203-000321	C-CERAMIC,CHIP;0.12nF,5%,50V,SL,TP,2012	
C345	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
C346	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C347	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C348	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C349	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	

Loc.No	Part No	Description ; Specification	Remark
C350	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C351	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C352	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C353	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C354	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C355	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	Not used SVR-557
C356	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	F/AV Option
C371	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C372	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C380	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C382	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A01	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A09	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012	
C3A10	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012	
C3A11	2301-000176	C-FILM,PEF;18nF,5%,100V,TP,10X9X4.3X5,5m	SVR-750/659/653
	2301-000174	C-FILM,PEF;15nF,5%,100V,TP,7.2x4.0x7.5mm	SVR-650/6503/557
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
C3A15	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A16	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201	
C3A21	2203-000170	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,2012	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A29	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A30	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3D01	2301-000415	C-FILM,PEF;22nF,5%,50V,TP,6.5x10.5x4mm,5	SVR-750/659/653 Only
C3D02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	SVR-750/659/653 Only
C3D03	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	SVR-750/659/653 Only
C3D04	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	SVR-750/659/653 Only
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P,1.25mm,STRAIGH	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25mm,STRAIGHT	
CN3A02	3710-001648	CONNECTOR-SOCKET;2P,1R,2.5mm,STRAIGHT,SN	
D1SS33	0404-001097	DIODE-SCHOTTKY;SG45,45V,7500mA,TO-220A,B	
D301	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6x6.4mm	
FL3D01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6x6.4mm	SVR-750/659/653 Only
IC301	1204-001923	IC-VIDEO PROCESS;LA71730M,QFP,100P,-,PLA	SVR-750/659/557
	1204-001922	IC-VIDEO PROCESS;LA71750M,QFP,100P,-,PLA	SVR-653/650/6503
L301	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L302	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L370	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A01	2702-000120	INDUCTOR-RADIAL;15mH,5%,6.2x7.4mm	
L3A02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A03	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L3A50	2702-000119	INDUCTOR-RADIAL;150uH,5%,6x6.4mm	SVR-750/659/653 Only
L3D01	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	SVR-750/659/653 Only
Q302	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q350	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3D01	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	SVR-750/659/653 Only
Q3D02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	SVR-750/659/653 Only
Q3D07	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	SVR-750/659/653 Only
R315	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R316	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R320	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R321	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R322	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R323	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
R324	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R328	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R329	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
R330	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R331	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
R333	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R334	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R336	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	F/AV Option
R350	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
R360	2007-000068	R-CHIP;470KOHM,5%,1/10W,DA,TP,2012	
R370	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R372	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R373	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R374	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R3A01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A04	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A05	2007-000615	R-CHIP;24KOHM,5%,1/10W,DA,TP,2012	
R3A06	2007-000449	R-CHIP;180OHM,5%,1/10W,DA,TP,2012	
R3A07	2007-000757	R-CHIP;330KOHM,5%,1/10W,DA,TP,2012	
R3A08	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R3A09	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R3A11	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A12	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R3A13	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	SVR-750/659/653
	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	SVR-650/6503/557
R3A14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A16	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3A17	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A18	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A23	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A24	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R3A25	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A28	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
R3A31	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R3A50	2007-000964	R-CHIP;5.1KOHM,5%,1/10W,DA,TP,2012	
R3A51	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3A60	2001-000605	R-CARBON;3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3D01	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	SVR-750/659/653 Only
R3D02	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	SVR-750/659/653 Only
R3D03	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	SVR-750/659/653 Only
R3D04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-750/659/653 Only
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15ppm,28-AAA,S,	SVR-750/659/557 Only
TM-BLOCK			
C401	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C402	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C403	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	Not used SVR-557
C405	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
C406	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C408	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C410	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
D410	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L402	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
R401	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R402	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R403	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R404	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R406	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R407	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R408	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
TM401	AC40-00014A	TM BLOCK;TCMK0601PD13A,G/I/K(MONO,HIFI)	SVR-750
	AC40-20100L	RF MODULATOR;RMUP74055VC,VCP PAL	SVR-557
	AC40-00015A	TM BLOCK;TMDG1-831A,PAL-G/I/K(MONO),-,-	Other Models
ZD401	0403-000390	DIODE-ZENER;UZP33B,33V,31.4-34.6V,1W,DO-	
HI-FI PARTS			
C501	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C502	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C503	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C504	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C505	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C506	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C507	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C508	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C510	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C511	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C513	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C517	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C518	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C519	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C520	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C521	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C522	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C523	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C524	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C525	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C530	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C541	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C542	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
L501	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
R501	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R502	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R503	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R505	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R506	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R507	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	F/AV Option
R508	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	F/AV Option
R509	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R510	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R511	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R512	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
R514	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R516	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R518	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R519	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	F/AV Option
R520	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	F/AV Option
R545	2007-000511	R-CHIP;2.4KOHM,5%,1/10W,DA,TP,2012	
R546	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R547	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R570	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R571	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
SECAM PARTS(SVR-750/659 Only)			
C3S01	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3S02	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S03	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3S04	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S05	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C3S06	2401-001775	C-AL;470nF,20%,50V,GP,TP,4x7,5	
C3S07	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C3S08	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3S09	2401-001775	C-AL;470nF,20%,50V,GP,TP,4x7,5	
C3S10	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3S11	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3S12	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C3S13	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C3S14	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C3S15	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
IC3S01	1204-001921	IC-CHROMA;LA70100M,SOP,30P,375MIL,PLASTI	
R3S01	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R3S02	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
OSD/PDC PARTS			
R6P07	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R6P08	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
R6P09	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
C6P01	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C6P02	2203-000321	C-CERAMIC,CHIP;0.12nF,5%,50V,SL,TP,2012	
C6P04	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P05	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P08	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C6P10	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P12	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C6P13	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
IC6P01	1204-001796	IC-OSD PROCESSOR;LC74759JM-9820,MFP,24P,	
L6P03	2701-000160	INDUCTOR-AXIAL;22uH,5%,2.4x3.4mm	
L6P05	2701-000165	INDUCTOR-AXIAL;27uH,5%,2.4x3.4mm	
Q6P01	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
R6P05	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P10	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
INPUT/OUTPUT PARTS			
C806	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C822	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C837	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C838	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C844	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C845	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
D805	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	SVR-750/659 Only
JC801	3722-001574	JACK-SCART;21P,-,SN,BLK,#20-28	SVR-750/659
	3722-001577	JACK-PIN;6P,3.5mm,NI,BLK,-	SVR-653/650/6503/557
JC802	3722-001576	JACK-PIN;2P,3.5mm,NI,BLK,-	SVR-750/659 Only
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	SVR-750/659 Only
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	SVR-750/659 Only
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
Q802	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	SVR-750/659 Only
Q804	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	SVR-750/659 Only
Q809	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R802	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	SVR-750/659 Only
R803	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	SVR-750/659 Only
R805	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	SVR-750/659 Only
R806	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	SVR-750/659 Only
R807	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R812	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
R813	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R814	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R815	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R816	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R828	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R842	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD807	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	SVR-659 Only
ZD810	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD811	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD812	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD813	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DISPLAY/FUNCTION MATRIX PARTS			
C701	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	Not used SVR-659
C702	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	Not used SVR-659
C703	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	Not used SVR-659
C750	2203-000335	C-CERAMIC,CHIP;0.012nF,5%,50V,NP0,TP,201	SVR-659 Only
C751	2203-000335	C-CERAMIC,CHIP;0.012nF,5%,50V,NP0,TP,201	SVR-659 Only
C752	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	SVR-659 Only
CN701	3711-004773	CONNECTOR-HEADER;3WALL,12P,1R,2mm,STRAIG	SVR-750 Only
	3711-004625	CONNECTOR-HEADER;3WALL,8P,1R,2mm,STRAIGH	SVR-659 Only
CN708	3711-004774	CONNECTOR-HEADER;3WALL,15P,1R,2mm,STRAIG	SVR-750 Only
	3711-004415	CONNECTOR-HEADER;3WALL,11P,1R,2mm,STRAIG	SVR-659/653 Only
D701	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D702	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D703	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D704	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D705	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	SVR-750 Only
DT701	AC07-00031A	LED DISPLAY;LTG-0129M,-,38,8,5,55.2*18.5	5DIGIT
	AC07-00039A	LED DISPLAY;C-384EG,-,38,8,5,52.8*18.5*2	4DIGIT
IC701	1003-001443	IC-LED DRIVER;PT6959,SOIC,28P,300MIL,-,-	Not used SVR-557
IC750	AC09-00315A	IC MICOM;789026GB-A81-8ES,V-652F-AVLINK	SVR-659 Only
L701	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	Not used SVR-557
R727	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R728	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R729	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R730	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R731	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	Not used SVR-659
R732	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R733	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R734	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	
R735	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R736	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R737	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R738	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R741	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	Not used SVR-557
R750	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	SVR-659 Only
R751	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	SVR-659 Only
R752	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	SVR-659 Only
R753	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R777	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	SVR-557 Only
R7S01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-557 Only
R7S02	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R7S03	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R7S04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7S05	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7S06	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	Not used SVR-659
XT750	2801-003868	CRYSTAL-UNIT;5MHz,30ppm,28-AAA,12pF,100o	SVR-659 Only

Loc.No	Part No	Description ; Specification	Remark
-	-	**ASSY PCB-FUNCTION;**	**S.N.A.**
C720	2201-000281	C-CERAMIC,DISC;1nF,+80-20%,50V,Y5V,TP,5x	
C721	2201-000281	C-CERAMIC,DISC;1nF,+80-20%,50V,Y5V,TP,5x	
CN704	3710-001691	CONNECTOR-SOCKET;15P,1R,2mm,ANGLE,SN	
CN705	3710-001692	CONNECTOR-SOCKET;12P,1R,2mm,ANGLE,SN	
JK701	AC37-00006A	JACK-PIN;3.2MM,DPSE-9872,3P,ARREY,10MM	
SW721	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW722	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW723	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW724	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW725	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW726	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW727	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW728	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW729	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW730	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW731	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW732	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW733	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW734	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW735	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW738	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW740	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
-	-	**ASSY PCB-SHUTTLE;SVR-653/557 Only**	**S.N.A.**
CN6B01	3708-001164	CONNECTOR-FPC/FFC/PIC;5P,1.25mm,ANGLE,SN	
SH6S1	2101-000101	VR-ROTARY;100Kohm,20%,1/10W,SIDE	
-	-	**ASSY PCB-LED SINGLE;SVR-557 Only**	**S.N.A.**
CN7F1	3711-003176	CONNECTOR-HEADER;NOWALL,10P,1R,2.5mm,ANG	
DT7F1	AC61-00153A	HOLDER-LED;SV-443F,ABS94HB,-,-,-,-,-	
INLAY	AC64-00680A	INLAY-LED;SV-G12K,PVC,0.5,-,-,-,-	
LD7F1	0601-001408	LED;ROUND,GRN,-,-	
LD7F2	0601-001408	LED;ROUND,GRN,-,-	
LD7F3	0601-001408	LED;ROUND,GRN,-,-	
LD7F4	0601-001201	LED;ROUND,RED,3mm,635nm	
LD7F5	0601-001408	LED;ROUND,GRN,-,-	
Q7F1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q7F2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q7F3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q7F4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q7F5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R7F1	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7F2	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7F3	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7F4	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7F5	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7F6	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	

4-2 SVR-453/450/4503/253/250/2503/155/1503/151

Loc.No	Part No	Description ; Specification	Remark
-	-	**ASSY PCB-MAIN FULL;**	**S.N.A.**
S.M.P.S. PARTS			
BD1SD1	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SD2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
BD1SF1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
BD1SF2	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SF3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS1	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS2	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD03	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SD04	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SD11	2401-001682	C-AL;82uF,20%,400V,GP,BK,22x25,10	
C1SD12	2305-001029	C-FILM,MPEF;10nF,10%,630V,TP,12x9x12.5,5	
C1SD13	2201-000376	C-CERAMIC,DISC;0.22nF,5%,50V,SL,TP,6.3x3	
C1SF12	2401-001200	C-AL;33UF,20%,50V,WT,TP,6.3X11,2.5	
C1SS01	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS02	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS03	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SS12	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1kV,Y5P,TP,7x4,	
C1SS31	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS32	2401-003137	C-AL;330UF,20%,50V,WT,TP,10X16MM,5	
C1SS33	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS34	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS35	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS36	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C1SS39	2301-000129	C-FILM,PEF;100nF,5%,50V,TP,10X9X4.3X5,5m	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SD11	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SD31	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SF05	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SF12	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS31	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS32	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,DO-204AC,TP	
D1SS33	0404-001097	DIODE-SCHOTTKY;SG45,45V,7500mA,TO-220A,B	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
IC1SF1	1203-001802	IC-PWM CONTROLLER;STR-G6551,TO-220F,5P,-	
IC1SS1	0604-000186	PHOTO-COUPLER;TR,-,200mW,DIP-4,ST	⚠
IC1SS2	AC14-12006D	IC;KA431Z,TO-92,TAPING	
L1SS02	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	⚠
L1SS31	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS32	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1SS1	AC26-00002C	TRANS SWITCHING;-,-,EE2621,-,UL/CSA/DEMK	⚠
R1SD12	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD13	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD14	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD15	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD16	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R1SD31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF15	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SF19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF20	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SF21	2001-000096	R-CARBON(S);1MOHM,5%,1/2W,AA,TP,2.4X6.4M	
R1SS03	2008-001033	R-FUSIBLE(S);10ohm,5%,2W,AF,TP,3.9x10mm	
R1SS10	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS11	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R1SS32	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R1SS33	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS34	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
VA1SS1	1405-001026	VARISTOR;470V,600A,9x7mm,TP	⚠
POWER DRIVE PARTS			
C1P102	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P103	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P104	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P105	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P106	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C1P120	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
D1P101	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
Q1P101	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P102	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P104	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
Q1P105	0504-000116	TR-DIGITAL;KSR1001,NPN,300MW,4.7K/4.7K,T	
R1P101	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P106	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P107	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R1P108	2001-000611	R-CARBON;3.9KOHM,5%,1/4W,AA,TP,2.4X6.4M	
R1P110	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R1P115	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZD1P04	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
SYSTEM CONTROL/SERVO PARTS			
C601	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C602	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C605	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C607	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	BACK-UP Option
C609	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C620	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C622	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2	
C623	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C624	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	BACK-UP Option
C625	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	BACK-UP Option
C626	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C627	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C633	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C634	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C635	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C636	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C637	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
C638	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
C639	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C640	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C641	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C642	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C644	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
C646	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C650	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C651	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C652	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C655	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
C679	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C680	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C681	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C690	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C691	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C692	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C693	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	SVR-453/450/4503 Only
C695	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
C697	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
CN604	3711-004833	CONNECTOR-HEADER;BOX,12P,2R,2MM,STRAIGHT	
D603	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D605	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D612	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC601	AC09-00316A	IC MICOM;784927GF-232-3BA,SVR-653,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001148	IC-EEPROM;24C021,2KBIT,DIP,8P,300MIL,10M	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	BACK-UP Option
L602	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L603	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
LD601	0601-000517	LED-IR;RECTANGULA,4x6.0mm,75mW,6V,950	
PT601	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
PT602	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
Q601	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R605	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R613	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	BACK-UP Option
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R631	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R632	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-450/450/4503 Only
R637	2007-000947	R-CHIP;47OHM,5%,1/10W,DA,TP,2012	
R638	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R639	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R641	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R642	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R644	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R651	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012	
R656	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R657	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	BACK-UP Option
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
R666	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R667	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R668	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R669	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R670	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R671	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R672	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R674	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2007-000738	R-CHIP;30KOHM,5%,1/10W,DA,TP,2012	
R678	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R679	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R680	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	BACK-UP Option
R682	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R685	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
R690	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R691	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R692	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	BACK-UP Option
R693	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R694	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R696	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R698	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RS601	AC34-20100B	SWITCH-REC;-,-,X-9,-	
S601	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
S602	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
SW601	AC34-20100A	SWITCH-MODE;-,-,X-9,-	
W062	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W064	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W066	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W088	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
W140	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	BACK-UP Option
XT602	2801-003139	CRYSTAL-UNIT;8MHz,50ppm,28-AAA,22pF,80oh	
AUDIO/VIDEO PARTS			
C315	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C317	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C318	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C319	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,	
C320	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C321	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C322	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C324	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C325	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C326	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C327	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
C328	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C329	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C330	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C331	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C332	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C333	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C335	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C336	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	F/AV Option
C337	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C338	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C339	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C344	2203-000321	C-CERAMIC,CHIP;0.12nF,5%,50V,SL,TP,2012	
C345	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
C346	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C347	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C348	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C349	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C350	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C351	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C352	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C353	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C354	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C355	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	Not Used SVR-155/1503/151
C356	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	F/AV Option
C371	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C372	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C380	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C382	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A01	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A09	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012	
C3A10	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012	
C3A11	2301-000174	C-FILM,PEF;15nF,5%,100V,TP,7.2x4.0x7.5mm	
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
C3A15	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A16	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201	

Loc.No	Part No	Description ; Specification	Remark
C3A21	2203-000170	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,2012	
C3A22	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A29	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A30	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A31	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	F/AV Option
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CN301	3708-000394	CONNECTOR-FPC/FFC/PIC,6P,1.25mm,STRAIGHT	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC,6P,1.25mm,STRAIGHT	
CN3A02	3710-001648	CONNECTOR-SOCKET;2P,1R,2.5mm,STRAIGHT,SN	
D301	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6x6.4mm	
IC301	1204-001922	IC-VIDEO PROCESS;LA71750M,QFP,100P-,PLA	
L301	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L302	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L370	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A01	2702-000120	INDUCTOR-RADIAL;15mH,5%,6.2x7.4mm	
L3A02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A03	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
Q350	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
R315	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R316	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R320	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R321	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R322	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R323	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
R325	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R328	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R329	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
R330	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R331	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
R333	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R334	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R335	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R336	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	F/AV Option
R360	2007-000068	R-CHIP;470KOHM,5%,1/10W,DA,TP,2012	
R370	2001-000857	R-CARBON;5600HM,5%,1/8W,AA,TP,1.8X3.2MM	
R372	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R373	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R374	2007-000290	R-CHIP;1000HM,5%,1/10W,DA,TP,2012	
R3A01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A04	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A05	2007-000615	R-CHIP;24KOHM,5%,1/10W,DA,TP,2012	
R3A06	2007-000449	R-CHIP;1800HM,5%,1/10W,DA,TP,2012	
R3A07	2007-000757	R-CHIP;330KOHM,5%,1/10W,DA,TP,2012	
R3A08	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R3A09	2007-000029	R-CHIP;00HM,5%,1/10W,DA,TP,2012	
R3A11	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A12	2007-000290	R-CHIP;1000HM,5%,1/10W,DA,TP,2012	
R3A13	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R3A14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A16	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3A17	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A18	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A23	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A24	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R3A25	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A27	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R3A28	2007-000964	R-CHIP;5.1KOHM,5%,1/10W,DA,TP,2012	
R3A29	2007-000964	R-CHIP;5.1KOHM,5%,1/10W,DA,TP,2012	F/AV Option
R3A31	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R3A32	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A33	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	F/AV Option
R3A50	2007-000964	R-CHIP;5.1KOHM,5%,1/10W,DA,TP,2012	
R3A51	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
TM-BLOCK			
C401	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C402	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C403	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	Not used SVR-155/1503/151
C405	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
C406	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C408	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C410	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
D410	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L402	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
R401	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R402	2007-000290	R-CHIP;1000HM,5%,1/10W,DA,TP,2012	
R403	2007-000290	R-CHIP;1000HM,5%,1/10W,DA,TP,2012	Not used SVR-155/1503/151
R404	2007-000290	R-CHIP;1000HM,5%,1/10W,DA,TP,2012	Not used SVR-155/1503/151
R406	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R407	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R408	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
TM401	AC40-00015A	TM BLOCK;TMDG1-831A,PAL-G/I/K(MONO),-,-	Other Models
	AC40-20100L	RF MODULATOR;RMUP74055VC,VCP PAL	SVR-155/1503/151 Only
ZD401	0403-000390	DIODE-ZENER;UZP33B,33V,31.4-34.6V,1W,DO-	
OSD/PDC PARTS			
C6P01	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C6P02	2203-000321	C-CERAMIC,CHIP;0.12nF,5%,50V,SL,TP,2012	
C6P04	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P05	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P08	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C6P10	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P12	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C6P13	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
IC6P01	1204-001796	IC-OSD PROCESSOR;LC74759JM-9820,MFP,24P,	
L6P03	2701-000160	INDUCTOR-AXIAL;22uH,5%,2.4x3.4mm	
L6P05	2701-000165	INDUCTOR-AXIAL;27uH,5%,2.4x3.4mm	
Q6P01	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
R6P05	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P07	2007-000572	R-CHIP;2200HM,5%,1/10W,DA,TP,2012	
R6P08	2007-000822	R-CHIP;3900HM,5%,1/10W,DA,TP,2012	
R6P09	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R6P10	2001-000515	R-CARBON;2200HM,5%,1/8W,AA,TP,1.8X3.2MM	
INPUT-OUTPUT PARTS			
C806	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C822	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C837	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C845	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
JC801	3722-001575	JACK-PIN;4P/6P,3.5mm,NI,BLK,-	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
Q809	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	

Loc.No	Part No	Description ; Specification	Remark
R807	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
R812	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
R813	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R814	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R815	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R816	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R828	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R842	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD812	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD813	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DISPLAY/FUNCTION MATRIX PARTS			
C701	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C702	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C703	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
CN703	3708-001163	CONNECTOR-FPC/FFC/PIC;5P,1.25mm,STRAIGHT	SVR-453/253/151 Only
CN708	3711-004415	CONNECTOR-HEADER;3WALL,11P,1R,2mm,STRAIG	F/AV Option
D701	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D702	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D703	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D704	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
DT701	AC07-00039A	LED DISPLAY;C-384EG,-,38,8,5,52.8*18.5*2	SVR-450/450/4503 Only
IC701	1003-001443	IC-LED DRIVER;PT6959,SOIC,28P,300MIL,-,-	SVR-450/450/4503 Only
L701	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	SVR-450/450/4503 Only
R727	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R728	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R729	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R730	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R731	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R732	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R733	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R734	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	
R735	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R736	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R737	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R738	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R741	2007-000658	R-CHIP;27OHM,5%,1/10W,DA,TP,2012	SVR-450/450/4503 Only
R753	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	F/AV Option
R777	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	BACK-UP Option
R7S01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	LED SUB DISPLAY Only
R7S02	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	LED SUB DISPLAY Only
R7S03	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	LED SUB DISPLAY Only
R7S04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	LED SUB DISPLAY Only
R7S05	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	LED SUB DISPLAY Only
R7S06	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	LED SUB DISPLAY Only
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW708	3404-001187	SWITCH-TACT;12V,50MA,100GF,6X6X9.5,SPST	
SW709	3404-001187	SWITCH-TACT;12V,50MA,100GF,6X6X9.5,SPST	
SW712	3404-001187	SWITCH-TACT;12V,50MA,100GF,6X6X9.5,SPST	
SW713	3404-001187	SWITCH-TACT;12V,50MA,100GF,6X6X9.5,SPST	
SW718	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW720	3404-001187	SWITCH-TACT;12V,50MA,100GF,6X6X9.5,SPST	
-	-	**ASSY PCB-F/AV;SVR-450/253 Only**	**S.N.A.**
C702	2201-000470	C-CERAMIC,DISC;330pF,10%,50V,SL,TP,6.5x3	
CN705	3710-001564	CONNECTOR-SOCKET;11P,1R,2mm,ANGLE,SN	
JC701	AC37-22002J	JACK-PIN;3.2mm,DPSE-9814,2P,13mm,S/W	
L705	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
SW706	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW730	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
-	-	**ASSY PCB-SHUTTLE;SVR-450/253/151 Only**	**S.N.A.**
CN6B01	3708-001164	CONNECTOR-FPC/FFC/PIC;5P,1.25mm,ANGLE,SN	
SH6S1	2101-000101	VR-ROTARY;100Kohm,20%,1/10W,SIDE	

Loc.No	Part No	Description ; Specification	Remark

MEMO